



# Limitimer®

## DIP Switch Settings Timer (PRO-2000 and AV-2000)



Roslyn Heights,  
NY



www.dsan.com/Limitimer

Tel: 516 625-5608  
info@dsan.com  
Made in USA

**1. SLAVE-MASTER**  
Master (ON) For dual control of signal lights. One timer must be master.

**2. COUNTING PROGRAM 4**  
MINUTES:SECONDS (ON)  
HOURS:MINUTES (OFF)

**3. COUNTING PROGRAMS 1,2,3**  
MINUTES:SECONDS (ON)  
HOURS:MINUTES (OFF)

**4. COUNTING DIRECTION**  
Count Down (ON)  
Count Up (OFF)

**PRO-2000 Quick Start**  
Set Total Time  
Set Sum-Up  
Press Start

**5. COUNTING BEHAVIOR**  
Continue after zero (ON), else stop counting.



**6. SOUND VOLUME**  
High (ON)

**7+8. SELECT BEEP SOUNDS**  
7-ON 8-ON None  
7-OFF 8-ON Buzz  
7-ON 8-OFF Ring  
7-OFF 8-OFF Chime

**9. SETTINGS PERMISSION**  
Allow time changes (ON) while clock runs

**10. TRANSMITTER**  
No Signal (OFF)  
  
Timer model PRO-2000RF can communicate with an unlimited number of receivers (RFR-2000). Channels not used.

**MODEL PRO-2000BT**  
11+12. WIRELESS COMMUNICATION  
Match Channels - Timer with Receiver


=


Default Settings  
PRO-2000BT can communicate with up to a total of 6 receivers (Model TR-2000BT) or other timers on each channel.

[Switch] = 2	Receiver channels 5,6,7,0 not used
[Switch] = 3	
[Switch] = 4	

Serial No.

## Podium Signal Light (PSL-20V and PSL-20VF)

**1-4. DISPLAY PROGRAMS**

**5. COUNT AFTER ZERO (ON)**

**6. VOLUME - HI (ON)**

7-OFF + 8-OFF = SILENT  
7-OFF + 8-ON = CHIME  
7-ON + 8-OFF = RING  
7-ON + 8-ON = BUZZ

**9. DISPLAY TOP LEDS (ON)**

**10. DISPLAY DIGITS (ON)**



PSL20V

D'San Corp.  
T: 516 625-5608  
www.dsan.com/  
Limitimer  
Made in USA

## Audience Signal Lights (ASLX-4ND3)

DISPLAY PROGRAMS				COUNT BEHAVIOR	CLOCK	N/A	N/A	CLOCK ENABLE
1	2	3	4	5	6	7	8	9
ON	*	*	*	* COUNT PAST 0:00	*12 HOUR			DISPLAY CLOCK WHEN TIMER IS OFF
OFF				STOP AT 0:00	24 HOUR			DISPLAY BLANK WHEN TIMER IS OFF

(\* = DEFAULT)

MODEL ASL4-ND3BT		
10	11	12
*	*	*
<small>Settings to receive data from wireless timer model PRO-2000BT 10 Turn transceiver on/off 11+12 Bluetooth® communications channels. Match with switches 11 + 12 on timer</small>		